

Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234
www.tripplite.com

# OmniVS 120V 1500VA 940W Line-Interactive UPS, Tower, USB port

MODEL NUMBER: OMNIVS1500







#### Description

Tripp Lite's OMNIVS1500 line interactive UPS system offers voltage regulation, surge suppression and battery support for personal computers, internetworking equipment and other sensitive electronics. Internal UPS batteries support entry level PC systems for up to 75 minutes during power failures so that connected equipment can be shut down without data loss. Automatic Voltage Regulation (AVR) circuits regulate brownouts as low as 75 and overvoltages up to 147 volts back to usable 120V levels without using battery power. Offers complete desktop power protection in an attractive black tower configuration. Includes 5 battery supported outlets for computer, monitor and vital system peripherals, plus 3 additional surge suppression only outlets for printers and other system accessories not requiring battery support. USB port enables optional unattended system shutdown without data loss in the case of extended power failure (USB cable included). PowerAlert software available via free download. HID-compliant USB port also enables integration with built-in power management and auto shutdown features of Windows and Mac OS X. Built-in data line suppression offers protection for equipment with single line TEL/DSL or network Ethernet connection. Built-in audible alarm and 5 front panel LEDs indicate status of line power, battery power, battery low/replace, voltage regulation and overload. 1500VA power handling ability supports entry-level PCs, network workstations, point-of-sale equipment, small business phone systems, audio/video equipment and home theater systems. Offers 4.5 minutes battery runtime with a full load of 1500VA and 11.5 minutes with a half load of 750VA. Supports hot-swappable battery replacement via built-in access panel.

### **Features**

- OMNIVS1500 Uninterruptible Power Supply offers voltage regulation, surge suppression and long lasting battery support
- Supports entry level PCs up to 75 minutes during blackouts to enable shutdown without data loss
- Regulates brownouts as low as 75V and overvoltages to 147V back to usable 120V nominal levels without using battery power
- 5 UPS battery supported outlets, plus 3 additional surge suppression only outlets
- USB port enables data-saving unattended shutdown when used with Tripp Lite's PowerAlert software, available via FREE download from www.tripplite.com/poweralert
- HID-compliant USB port also enables integration with built-in power management and auto shutdown

#### **Highlights**

- 1500VA / 1.5kVA tower 120V line-interactive UPS
- Corrects brownouts and overvoltages from 75 to 147V
- 5 UPS battery supported outlets,
   3 surge-only outlets
- USB port, TEL/DSL/Ethernet protection, 97% line mode efficiency
- NEMA 5-15P input plug and 8
   NEMA 5-15R outlets

#### **Package Includes**

- OMNIVS1500 Line-Interactive UPS
- USB and telephone cable
- Owner's manual with warranty information



features of Windows and Mac OS X

- Data line surge suppression protects standard dialup/DSL or ethernet line connection
- Built-in audible alarm and 5 front panel LEDs indicate status of line power, battery power, battery low/replace, voltage regulation and overload
- 1500VA power handling ability supports a variety of sensitive electronic equipment
- 4.5 minutes full load runtime (1500VA), 11.5 minutes half load runtime (750VA)
- Supports hot swappable battery replacement via built-in access panel
- Optional PDUB15 bypass PDU enables hot-swappable UPS replacement with no disruption to connected equipment

## **Specifications**

OVERVIEW		
UPC Code	037332126382	
UPS Type	Line-Interactive	
OUTPUT		
Output Volt Amp Capacity (VA)	1500	
Output kVA Capacity (kVA)	1.5	
Output Watt Capacity (Watts)	940	
Nominal Voltage Details	120v nominal output in battery mode	
Frequency Compatibility	60 Hz	
Output Voltage Regulation (Line Mode)	-18%, +8%	
Output Voltage Regulation (Battery Mode)	+/- 5%	
UPS Output Receptacles (Surge Suppression Only)	5 UPS outlets, 3 surge-only outlets	
Hot-Swap PDU options	PDUB15 (2U / 8 5-15R outlets)	
Output AC Waveform (AC Mode)	Sine wave	
Output AC Waveform (Battery Mode)	PWM sine wave	
Nominal Output Voltage(s) Supported	110V; 115V; 120V	
Output Receptacles	(8) 5-15R	
Individually Controllable Load Banks	No	
INPUT		
Rated input current (Maximum Load)	12A	





Nominal Input Voltage(s) Supported	120V AC	
UPS Input Connection Type	5-15P	
UPS Input Cord Length (ft.)	6	
UPS Input Cord Length (m)	1.8	
Recommended Electrical Service	15A 120V	
Input Phase	Single-Phase	
Input Frequency	60Hz +/-5%	
BATTERY		
Full Load Runtime (min.)	4.5 min. (940w)	
Half Load Runtime (min.)	11.5 min. (470w)	
DC System Voltage (VDC)	24	
Battery Recharge Rate (Included Batteries)	Less than 4 hours from 10% to 90%	
Internal UPS Replacement Battery Cartridge	<a class="productLink" href="//www.tripplite.com/UPS-Replacement-24VDC-Battery-Cartridge-for-select-Tripp-Lite-SLT-UPS~RBC24-SLT">RBC24-SLT</a>	
Battery Access	Battery access door	
Battery Replacement Description	Hot-swappable, user replaceable batteries	
Expandable Runtime	No	
1		
VOLTAGE REGULATION		
	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 75 to 147	
VOLTAGE REGULATION	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 75 to 147 Input voltages between 128 and 147 are reduced by 12%	
VOLTAGE REGULATION  Voltage Regulation Description		
VOLTAGE REGULATION  Voltage Regulation Description  Overvoltage Correction	Input voltages between 128 and 147 are reduced by 12%	
VOLTAGE REGULATION  Voltage Regulation Description  Overvoltage Correction  Undervoltage Correction	Input voltages between 128 and 147 are reduced by 12% Input voltages between 93 and 107 are boosted by 14% Input voltages between 75 and 92 are boosted by 30%	
VOLTAGE REGULATION  Voltage Regulation Description  Overvoltage Correction  Undervoltage Correction  Severe Undervoltage Correction	Input voltages between 128 and 147 are reduced by 12% Input voltages between 93 and 107 are boosted by 14% Input voltages between 75 and 92 are boosted by 30%	
VOLTAGE REGULATION  Voltage Regulation Description  Overvoltage Correction  Undervoltage Correction  Severe Undervoltage Correction  USER INTERFACE, ALERTS & CON	Input voltages between 128 and 147 are reduced by 12%  Input voltages between 93 and 107 are boosted by 14%  Input voltages between 75 and 92 are boosted by 30%  TROLS	
VOLTAGE REGULATION  Voltage Regulation Description  Overvoltage Correction  Undervoltage Correction  Severe Undervoltage Correction  USER INTERFACE, ALERTS & CON  Switches	Input voltages between 128 and 147 are reduced by 12%  Input voltages between 93 and 107 are boosted by 14%  Input voltages between 75 and 92 are boosted by 30%  TROLS  2 Switches control off/on power status and alarm-cancel/self-test operation  Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-	
VOLTAGE REGULATION  Voltage Regulation Description  Overvoltage Correction  Undervoltage Correction  Severe Undervoltage Correction  USER INTERFACE, ALERTS & CON  Switches  Alarm Cancel Operation	Input voltages between 128 and 147 are reduced by 12%  Input voltages between 93 and 107 are boosted by 14%  Input voltages between 75 and 92 are boosted by 30%  TROLS  2 Switches control off/on power status and alarm-cancel/self-test operation  Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status	
VOLTAGE REGULATION  Voltage Regulation Description  Overvoltage Correction  Undervoltage Correction  Severe Undervoltage Correction  USER INTERFACE, ALERTS & CON Switches  Alarm Cancel Operation  Audible Alarm	Input voltages between 128 and 147 are reduced by 12%  Input voltages between 93 and 107 are boosted by 14%  Input voltages between 75 and 92 are boosted by 30%  TROLS  2 Switches control off/on power status and alarm-cancel/self-test operation  Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status  Audible alarm indicates power-failure and low-battery conditions	
VOLTAGE REGULATION  Voltage Regulation Description  Overvoltage Correction  Undervoltage Correction  Severe Undervoltage Correction  USER INTERFACE, ALERTS & CON  Switches  Alarm Cancel Operation  Audible Alarm  LED Indicators	Input voltages between 128 and 147 are reduced by 12%  Input voltages between 93 and 107 are boosted by 14%  Input voltages between 75 and 92 are boosted by 30%  TROLS  2 Switches control off/on power status and alarm-cancel/self-test operation  Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status  Audible alarm indicates power-failure and low-battery conditions	
VOLTAGE REGULATION  Voltage Regulation Description  Overvoltage Correction  Undervoltage Correction  Severe Undervoltage Correction  USER INTERFACE, ALERTS & CON  Switches  Alarm Cancel Operation  Audible Alarm  LED Indicators  SURGE / NOISE SUPPRESSION	Input voltages between 128 and 147 are reduced by 12% Input voltages between 93 and 107 are boosted by 14% Input voltages between 75 and 92 are boosted by 30%  TROLS  2 Switches control off/on power status and alarm-cancel/self-test operation  Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status  Audible alarm indicates power-failure and low-battery conditions  5 LEDs indicate line power, battery power, overload, voltage regulation and battery low/replace status	
VOLTAGE REGULATION  Voltage Regulation Description  Overvoltage Correction  Undervoltage Correction  Severe Undervoltage Correction  USER INTERFACE, ALERTS & CON  Switches  Alarm Cancel Operation  Audible Alarm  LED Indicators  SURGE / NOISE SUPPRESSION  UPS AC Suppression Joule Rating  UPS AC Suppression Response	Input voltages between 128 and 147 are reduced by 12% Input voltages between 93 and 107 are boosted by 14% Input voltages between 75 and 92 are boosted by 30%  TROLS  2 Switches control off/on power status and alarm-cancel/self-test operation  Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status  Audible alarm indicates power-failure and low-battery conditions  5 LEDs indicate line power, battery power, overload, voltage regulation and battery low/replace status	



PHYSICAL		
Installation Form Factors Supported with Included Accessories	Tower	
Installation Form Factors Supported with Optional Accessories	Wallmount (UPSWM - tower mounting kit)	
Primary Form Factor	Tower	
Primary UPS Depth (mm)	191	
Primary UPS Height (mm)	300	
Primary UPS Width (mm)	183	
Shipping Dimensions (hwd / cm)	37.59 x 27.43 x 27.94	
Shipping Dimensions (hwd / in.)	14.80 x 10.80 x 11.00	
Shipping Weight (kg)	13.15	
Shipping Weight (lbs.)	29.00	
UPS Housing Material	Polycarbonate	
UPS Power Module Dimensions (hwd, cm)	29.97 x 18.29 x 19.05	
UPS Power Module Dimensions (hwd, in.)	11.8 x 7.2 x 7.5	
UPS Power Module Weight (kg)	10.07	
UPS Power Module Weight (lbs.)	22.2	
ENVIRONMENTAL		
Operating Temperature Range	+32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius	
Storage Temperature Range	+5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius	
Relative Humidity	0 to 95%, non-condensing	
AC Mode BTU / Hr. (Full Load)	109	
Battery Mode BTU / Hr. (Full Load)	523	
AC Mode Efficiency Rating (100% Load)	97%	
COMMUNICATIONS		
Communications Interface	USB (HID enabled)	
PowerAlert Software	For local monitoring via the UPS's built-in USB port, download PowerAlert Local software at http://www.tripplite.com/poweralert	
Communications Cable	USB interface cable included	
WatchDog Compatibility	Supports Watchdog application, OS and hard-reboot restart options for remote applications	
Network UPS Tools Compatibility	NUT compatible. See the full list of Tripp Lite NUT compatible UPS systems at NUT UPS Compatibility Lis	
LINE / BATTERY TRANSFER		





Transfer Time	2-4 milliseconds	
Low Voltage Transfer to Battery Power (Setpoint)	75	
High Voltage Transfer to Battery Power (Setpoint)	147	
SPECIAL FEATURES		
Cold Start (Startup in Battery Mode During a Power Failure)	Cold-start operation supported	
High Availability UPS Features	Hot swappable batteries	
Green Energy-Saving Features	Greater than 95% efficiency - GREEN UPS	
CERTIFICATIONS		
UPS Certifications	Tested to UL1778 (USA); Tested to CSA (Canada); Tested to NOM (Mexico); Meets FCC Part 15 Category B (EMI)	
WARRANTY		
Product Warranty Period (U.S. & Canada)	3-year limited warranty	
Product Warranty Period (Latin America)	3-year limited warranty	
Product Warranty Period (International)	2-year limited warranty	
Product Warranty Period (Mexico)	3-year limited warranty	
Connected Equipment Insurance (U.S., Canada & Puerto Rico)	\$200,000 <a class="insuranceLink" href="//www.tripplite.com/support/insurance-policy">Ultimate Lifetime Insurance</a>	

© 2019 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: <a href="https://www.tripplite.com/products/product-certification-agencies">https://www.tripplite.com/products/product-certification-agencies</a>